



Switch Between Two DisplayPort Sources



EXT-DPKVM-241

Switch Between Two DisplayPort Sources

Switch between two computers effortlessly using the Gefen 2x1 DisplayPort KVM Switcher, utilizing one display and one USB 2.0 port for a keyboard and mouse. Switch audio, video, and control signals for each computer. Access two computers from one workstation without having to use a network. Switch through the front panel "select" button, using the supplied IR remote control or via the RS232 port. The Gefen DisplayPort KVM Switcher is compatible with both Macintosh and PC keyboards, mice, and displays.

How It Works

Connect a DisplayPort display and USB 2.0 keyboard/mouse to the Gefen DisplayPort KVM Switcher output. Connect DisplayPort, USB, and audio ports on both computers to the Gefen DisplayPort KVM Switcher input using the supplied cables.

Note: If the source and/or display is not DisplayPort compliant, a protocol-specific protocol adapter will be required in order to connect the source to the Switcher and/or the Switcher to the high-resolution display.

Features:

- Switches one High-Resolution Display between two DisplayPort-equipped computers with audio/video and USB keyboards
- Supports resolutions up to 2560 x 1600
- Supports RGB and YCbCr color spaces
- DisplayPort utilizes a compact connector for easier installations
- 1U tall, half-rack width enclosures are rack-mountable using EXT-RACK-1U

Specifications:

- Maximum Pixel Clock: 360 MHz
- Maximum Resolution: 2560x1600
- Input Connector: (2) DisplayPort (from computers)
- Output Connector: (1) DisplayPort (to display)
- Input Connector: (2) USB 2.0 Type "B" (from computers)
- Output Connector: (2) USB 2.0 Type "A" (to keyboard/mouse)
- Input Connector: (2) 3.5mm analog L/R audio (from computers)
- Output Connector: (1) 3.5mm analog L/R audio (to speakers or amplifier)
- Color Spaces: RGB and YCbCr
- Dimensions: 8.41"W x 1.57"H x 4.23"D
- Shipping Weight: 6 lbs.

Gefen, LLC

20600 Nordhoff Street, Chatsworth CA 91311
Tel. (818) 772-9100 (800) 545-6900 Fax (818) 772-9120
www.gefen.com

*Features and specifications are subject to change without notice.
All trademarks and registered trademarks are properties of their respective owners.